

JUMPER EINSTELLUNGEN / JUMPER ADJUSTMENT LED Converter 580138

 SW2

 SW
 SW1


 LED-OUT
 $U_{max} = 7,5V$
 $I_{const} = 120-700mA$
 1 bis 2 LED

 **LED Converter**
 **EC-48-LED-100-7**

● tc max. 60°C
ta= -20°C...+50°C
CE


Eingang / Input
40-48V 50/60Hz 14,6VA
40-48V DC 10,4W
max 2,5mm Ø l=8mm

Achtung!
Attention!
48V



Zur Verwendung in Anlagen nach
DIN EN 50172 (VDE 0108 Teil 100)
mit Zentralbatterieanlagen nach
DIN EN 50171 670381-V01

ACHTUNG / ATTENTION

Bitte beachten Sie, dass der LED-Converter durch Stecken der Jumper auf die Leistung der LED wie folgt einzustellen ist:		Please note that the LED converter by inserting the jumper on the power of the LED is set as follows:		
Leuchtmittel	Illuminant	Einstellung/ Adjustment Converter	Span- nung	Strom
LED Zeile - 2x3 LEDs zweiseitig	LED bar - 2x3 LEDs double-sided		6-6,7V	150mA
LED Zeile - 6 LEDs einseitig LED Zeile - 8 LEDs einseitig LED Zeile - 2x4 LEDs zweiseitig	LED bar - 6 LEDs oneside LED bar - 8 LEDs oneside LED bar - 2x4 LEDs double-sided		6-6,7V	220mA
LED Zeile - 3 LEDs einseitig LED Zeile - 12 LEDs einseitig LED Zeile - 2x6 LEDs zweiseitig	LED bar - 3 LEDs oneside LED bar - 12 LEDs oneside LED bar - 2x6 LEDs double-sided		6-6,7V	285mA
LED Zeile - 4 LEDs einseitig LED Zeile - 16 LEDs einseitig LED Zeile - 2x8 LEDs zweiseitig	LED bar - 4 LEDs onesided LED bar - 16 LEDs onesided LED bar - 2x8 LEDs double-sided		6-6,7V	400mA
Power LED - 1 St. 3 W Power LED - 2 St. 3 W	Power LED - 1 pc 3W Power LED - 2 pcs 3W		3-3,4V 6-6,7V	550mA

**Eine falsche Einstellung am Converter kann zur frühzeitigen
Zerstörung der LED führen!**

**An incorrect adjustment at the converter could result in
Destruction of LED!**